



Mixer

TS-20PD-4



Description:

The digital mixer adopts 32-bit floating-point DSP audio processor, and 24bit/48Khz digital-to-analog/analog-to-digital conversion. It supports 31-band GEQ processor, compressor, noise gate, delay, polarity, DSP effect, AUX, SUB, and LED level indication, load/save/copy mixer settings, remote control, USB interface, etc. It has 20 linear level inputs and 16 microphone preamplifiers and replay engines. It is suitable for all kinds of performance venues, conference rooms, schools, intelligent buildings, enterprises and also personal use.

Feature:

- * Built-in efficient DSP audio processor, super processing capacity, built-in 7 CPU chips, more powerful computing and processing capability.
- * Built-in dual digital audio processor enables users to freely edit the effect mode, sound depth and others.
- * 16 channels of MIC and LINE joint input interface and 16 microphone pre-amplifiers support connecting to all types of microphones; microphone input interface supports 48V phantom power.
- * 4 linear input interface can connect to stereo devices.
- * 8 breakpoint insertion can connect to additional processors(compressor, EQ, de-esser, filter).
- * Provide 2 sets of stereo main outputs, 4 sets of outputs, 4 auxiliary outputs, 1 set of stereo monitoring output, 2 headphone monitoring outputs.
- * A 7-inch LCD HD color touch screen, visualized operation interface and function settings, resolution: 1024 × 600.
- * The input channel supports 4-band parameter equalization; the output channel supports 31-band graphical equalization.
- * A high precision electric fader with 100mm stroke. Each input channel can be set before or after the fader.
- * Built-in 2 USB ports for stereo recording/playback/system upgrade.
- * 1 network interface, for firmware update or connecting to Ipad for remote control.
- * Support scene memory function, save and call 24 scenes.
- * Support DCA grouping function, several input signals can be grouped into 1 group to control the volume, and 6 groups of DCA are supported.
- * Support replication function, can quickly debug and set the channels; support lock, unlock, password modification functions, effectively prevent wrong operations.
- * Optional: DANTE network audio interface or USB multi-track audio interface.

Specification:

Model	TS-20PD-4
MIC and LINE joint input	16 channels (they are all XLR/single-plug hybrid interface)
Linear input	4-channel stereo single-plug interface
Intelligent output	2 sets of stereo main outputs, 4 group outputs, 4 auxiliary outputs, 1 set of stereo monitoring output, 2 headphone monitoring outputs
INSERT	8-channel breakpoint insertion connect to additional processor
USB interface	2 USB ports for stereo recording/playback/system update
Screen	7-inch HD IPS touch screen, resolution: 1024×600
AD/DA	Support 24bit/48Khz
DSP processor	32-bit floating point
Phantom power	+48VDC
Frequency response direct output	20Hz~20KHz at 0dB±1.5dB
Distortion	<0.01% at 0dB±1KHz
SNR	104dB
Maximum input level	+22dB
Linear input gain	-15dB~+35dB
Audio processor	12 effects: Hall, Room, Plate, Delay, Stdelay, Tremolo, Flanger, Chorus, DelayRev, StdelayRev, FlangerRev, ChorusRev
Noise gate	Threshold range: -84dBu-0dB; start time: 0.5ms-200ms; release time: 5ms-2000ms
Compressor	Threshold range: -30dBu+20dB; start-up time: 10ms-150ms; release time: 10ms-1000ms; ratio: 1:1to24:1; gain: 0dBu+24dB
Equalizer	21Hz-19.2KHz +/-24dB
ADC, DAC dynamic range	114dB
Internet	Network port, with external router, can connect to ipad for remote control
Power voltage	AC 90-240V 50/60Hz power supply
Working temperature	Working temperature 0-40°C, storage temperature -20-60°C
Size	460×370×150mm
Weight	7.78Kg